




Типоразмеры

Типоразмеры преобразователи частоты малой и средней мощности

Типоразмер	A1		A2		A3		A5	B1	B2	B3	B4	C1	C2	C3	C4
															
IP	20	21	20	21	20	21	55/66	21/55/66	21/55/66	20	20	21/55/66	21/55/66	20	20
Высота (мм)	200	307	246	372	246	372	420	480	650	350	460	680	770	490	600
Ширина (мм)	75	75	90	90	130	130	242	242	242	165	231	308	370	308	370
Глубина (мм)	205	205	205	205	205	205	200	260	260	248	242	310	335	333	333
Макс. вес (кг)	2,7		4,9	5,3	6,6	7,0	14	23	27	12	12,5	45	65	35	50

Типоразмеры преобразователи частоты большой мощности

Типоразмер	D1	D2	D3	D4	E1	E2	F1	F2	F3	F4
			 130B A478.10	 130B A479.10		 130B A480.10				
IP	21/54	21/54	00	00	21/54	00	21/54	21/54	21/54	21/54
Высота (мм)	1159	1540	997	1277	2000	1547	2204	2204	2204	2204
Ширина (мм)	420	420	408	408	600	585	1400	1800	2000	2400
Глубина (мм)	373	373	373	373	494	498	606	606	606	606
Макс. вес (кг)	104	151	91	138	313	277	1004	1246	1299	1541

Примечание. Габариты указаны без учёта опций (подробнее смотри соответствующую инструкцию по эксплуатации).